

FLUORESCENT FLUSH MOUNT FIXTURE ASSEMBLY & INSTALLATION INSTRUCTIONS

Please read carefully and save these instructions, as you may need them at a later date.

CAUTION

Turn off the main power at the circuit breaker before installing the fixture, in order to prevent possible shock.

GENERAL

All electrical connections must be in accordance with local and national electrical code (N.E.C) standards. If you are unfamiliar with proper electrical wiring connections obtain the services of a qualified electrician.

Remove the fixture and the mounting package from the box and make sure that no parts are missing by referencing the illustrations on the installation instruction.

ASSEMBLY AND INSTALLATION

1. Take off the Wire Guard(2) from the Fixture Panel(1). (See Fig. 1)
2. Insert the Wire Connecting Panel(3) into the through of the middle of Fixture Panel(1), be sure to keep the holes in consistency, affix using Screws(4). (See Fig. 2)
3. Attach the small loops of the "S" Hooks(6) to an end of each Support Chain(5). Feed the large loops of the "S" Hooks(6) through the provided holes of the Channel. Close both ends of each "S" Hooks(6) using pliers. (See Fig. 3)
4. Replace Electronic Ballast: twist off Screws(8) and lift the EB Plate(7), then replace the EB and fix Screws(8). (See Fig. 4)
5. Select the desired installation location. Be sure that a standard 120V~277V 60Hz outlet is located within reach of the fixture's power cord. Install two hooks on the desired location of the ceiling. Be sure to install the ceiling hooks no more than fixture length apart. Install the fixture to the ceiling by looping the center of each Support Chain(5) to each ceiling-installed hook.

6. Make the wiring connections: connect the house ground wire to the fixture ground wire using wire connector (provided). Connect the white supply wire to the white fixture wire; Connect black supply wire to the black fixture wire using Power Plug (9). (See Fig.5)
7. Install the fluorescent lamps into the fixture socket. Be sure to use the correct type and wattage lamps, which are specified on the provided label on the fixture.

